

HFI-SS

Display Lighting

- Amazing 3D effect from the shade.
- The HFI T8 Stick-Lite, Stand and Shade can all be bought separately if required.
- Twelve Shade colours/types available.
- Shades can be printed with corporate logos, pictures or designs, POA.
- Different sizes available.
- Lamp and base colour in white, other colours available please enquire.
- Other shade designs/effects are available for bespoke applications, please enquire.



EncapSulite
Australia



For Product support Freecall 1800 733 113 or Email info@yld.com.au
Please see over for installation/instructions.

HFI-SS

Display Lighting

TECHNICAL INFORMATION:

For indoor applications only

POWER CABLE

0.75mm 2 core flat PVC HO3VVH2-F 300/300v. C7 and C8 plugs with Euro CEE7/16 plug, or 3amp fused UK plug BS1363A. Internal wiring PFA 2 x 0.59mm 240v RMS BS3G210. The external cable or cord of this luminaire cannot be replaced; if the cable or cord is damaged, the luminaire shall be destroyed.

VOLTAGE

220v-240v AC 50-60Hz, start up amps 0.98 operating amps 0.07 – 0.30 dependant on wattage.

STANDARDS

Lamp holders EN60400. Outer casing RT1 125, UL94 glow wire test 850c IEC695-2-1. End caps UL V2. Class 2 product, EN55015 EN50082-1 EN61000-3-2. Covers EMC/LV requirements, CE WEEE and ROHS compliant. BS 4533: 102.1: 1990/ EN 60598-2-1: 1989 & BS EN60598-1: 2008. DO NOT INSULATE LAMP.

RE-LAMPING

Disconnect power supply prior to re-lamping. Remove end cap opposite the cable end by twisting and pulling. Pull off lamp holder, pull lamp directly out do not twist, use pliers if necessary. Replace new lamp of the same type and wattage only, check orientation of lamp holder and lamp pins and slide new lamp in, use light pressure and twisting motion to locate lamp pins in lamp holder. Fit lamp holder on to lamp pins and re-fit end cap so locators inside of end cap locate in holes in tubing.

Plug and cable supplied as standard, foot switch cost option.



Wattage	Max Height	Shade Diameter	Base Diagonal
18w	800mm	210mm	245mm
36w	1530mm	210mm	345mm
58w	1830mm	210mm	345mm
70w	2100mm	210mm	345mm



For Product support Freecall 1800 733 113 or Email info@yld.com.au

See HFI-PS leaflet for printed shade information










HFI-SS

Display Lighting



TECHNICAL INFORMATION:

COLOURS



HFI-SS

Display Lighting

TECHNICAL INFORMATION:

CONSTRUCTION DETAILS

- Insert stick-lite into stand.
- Push plug through hole.
- Slide O rings down lamp, push O ring into top of stand. This keeps the lamp straight in the stand.
- Lay out shade, fit ends, clear end at bottom, white end at top with rings on the inside. Roll shade around ends ensuring locators fit through holes in the shade. Slide shade over the top of the light, locate the slot on the end of the shade on the end cap of the light.

